

**20004601****3IN/3OUT BUS MODULE, FLUSH/DIN RAIL MOUNT**

Interface on SimpleHome bus with 3 inputs and 3 outputs (configurable), comprising 1 16A NO/NC relay and 2 with transistors for controlling an external relay Art. 20004603. For flush or DIN-rail mounting. Dimensions: 42x42x18mm (1 DIN module). Max input current: 115mA.


20004601

3IN/3OUT BUS MODULE, FLUSH/DIN RAIL MOUNT

MAIN FEATURES

Flush-mounted	Yes
DIN rail mounted	Yes

FUNCTIONS

Rolling shutter/Venetian blind control	Yes
Timed output management	Yes
Digital inputs configured via software nc/no	Yes
BUS address programming via dip-switch	Yes
Configurable no/nc outputs	Yes
Automation management	Yes
Loads management	Yes
Climate management	Yes
Lights management	Yes
Scenario management	Yes

GENERAL DATA

Height (mm)	42
Width (mm)	42
Depth (mm)	18

COMPATIBILITY

Home Automation system	Yes
------------------------	-----

MOUNTING/INSTALLATION

DIN modules (no.) (n°)	1
------------------------	---

CONNECTIVITY

No. of Simplehome buses (n°)	1
------------------------------	---



20004601

3IN/3OUT BUS MODULE, FLUSH/DIN RAIL MOUNT

CONNECTIVITY

Digital inputs (n°)	3
Max distance from digital input (m)	25
Transistor output	2÷50mA max

TECHNICAL CHARACTERISTICS

Power supply from SimpleHome BUS	Yes
Maximum resistive load of a single output (mA)	10
Output status LEDs	Yes
Number of digital inputs (n°)	2
Number of scenario inputs (n°)	1
Number of outputs (n°)	3