

PIR & Smoke Detector Hidden Cameras

JCC-653

1/3" Color Sony CCD PIR Camera



JCC-653PA

1/3" Color Sony CCD PIR Camera with PIR Sensor & Audio



Features

- 1/3" Sony Color CCD Sensor
- NTSC: 811(H) x 508(V)
PAL: 795(H) x 596(V)
480 TV Lines / 0.5 Lux@F2.0
- Auto Gain Control
- Auto Electronic Shutter
- 0.45 Gamma Correction
- 3.7mm / F2.0 Pinhole Cone Lens Built-in
- DC 12V
- Optional with PIR Sensor & Audio Built-in (for JCC-653PA Model)

Specification

Model	JCC-653	JCC-653PA
Image Sensor	1/3" Sony Super HAD CCD Sensor(High Res.)	
Picture Element	NTSC: 811(H) x 508(V) ; PAL: 795(H) x 596(V)	
Synchronization	Internal	
Resolution	Horizontal 480 TV Lines	
Low-light Sensitivity	0.5 Lux @F2.0	
S/N Ratio	More than 48 dB (AGC OFF)	
Electronic Shutter	Auto: 1/60 (50) sec. ~ 1/100,000 sec	
White Balance	Auto White Balance (AWB)	
Gain Control	Auto Gain Control (AGC)	
Lens Built-in	3.7mm/F2.0 Pinhole Cone Lens	
Video Output	1.0 Vp-p Composite Video Output ; 75 Ohm	
Power Supply	DC 12V /160mA	
Operating Temperature	- 10 ~ 50 °C(14 ~ 122 °F)	
Audio Output	---	2V p-p 50Ω(RCA)
Built-in PIR Sensor	---	Yes
PIR NC/NO Relay Output	---	1 A /AC 125 V, 2A /DC 30 V
PIR Relay Alarm Time	---	2 ~ 40 sec. Adjustable
PIR Detection Angle	---	Hor. = 100 / Vert. = 45 degree
PIR Detection Range	---	Max. 10 Meters

Dimension

